

AWG gauge	Diameter inches	Diameter mm	Ohms per 1000 ft	Ohms per km	Max amps chassis wiring	Max amps power transmission
OOOO	0.46	11.684	0.049	0.16072	380	302
OOO	0.4096	10.40384	0.0618	0.202704	328	239
OO	0.3648	9.26592	0.0779	0.255512	283	190
0	0.3249	8.25246	0.0983	0.322424	245	150
1	0.2893	7.34822	0.1239	0.406392	211	119
2	0.2576	6.54304	0.1563	0.512664	181	94
3	0.2294	5.82676	0.197	0.64616	158	75
4	0.2043	5.18922	0.2485	0.81508	135	60
5	0.1819	4.62026	0.3133	1.027624	118	47
6	0.162	4.1148	0.3951	1.295928	101	37
7	0.1443	3.66522	0.4982	1.634096	89	30
8	0.1285	3.2639	0.6282	2.060496	73	24
9	0.1144	2.90576	0.7921	2.598088	64	19
10	0.1019	2.58826	0.9989	3.276392	55	15
11	0.0907	2.30378	1.26	4.1328	47	12
12	0.0808	2.05232	1.588	5.20864	41	9.3
13	0.072	1.8288	2.003	6.56984	35	7.4
14	0.0641	1.62814	2.525	8.282	32	5.9
15	0.0571	1.45034	3.184	10.44352	28	4.7
16	0.0508	1.29032	4.016	13.17248	22	3.7
17	0.0453	1.15062	5.064	16.60992	19	2.9
18	0.0403	1.02362	6.385	20.9428	16	2.3
19	0.0359	0.91186	8.051	26.40728	14	1.8
20	0.032	0.8128	10.15	33.292	11	1.5
21	0.0285	0.7239	12.8	41.984	9	1.2
22	0.0254	0.64516	16.14	52.9392	7	0.92
23	0.0226	0.57404	20.36	66.7808	4.7	0.729
24	0.0201	0.51054	25.67	84.1976	3.5	0.577
25	0.0179	0.45466	32.37	106.1736	2.7	0.457
26	0.0159	0.40386	40.81	133.8568	2.2	0.361
27	0.0142	0.36068	51.47	168.8216	1.7	0.288
28	0.0126	0.32004	64.9	212.872	1.4	0.226
29	0.0113	0.28702	81.83	268.4024	1.2	0.182
30	0.01	0.254	103.2	338.496	0.86	0.142